

REPLACEMENT PARTS LIST

PART NO.	PART NAME	SPECIFICATIONS	SYMBOLIC OR EXPLODED VIEW NO.
ACCN019GEA	CONN CORD ASSY.		
ACCN020GEA	CONN CORD ASSY.		
APTBM134UG	P.W. BOARD ASSY.		
APTLD010DA	P.W. BOARD ASSY.		
APTSW154HA	P.W. BOARD ASSY.		
CCDE151K0M	CERAMIC CAP.	150 pF 500V	C201
CEAGR22ZMN	ELYT. CAPACITOR	0.22 μ F 50V MS	C216
CKDB103PEM	CERAMIC CAP.	0.01 μ F 50V	C202/C203/C205/C207/C210/C211
CKDB472PEM	CERAMIC CAP.	4700 pF 50V	C208/C209/C212/C213/C214/C217
CKDB473ZFM	CERAMIC CAP.	0.047 μ F 50V	C204/C206
CQMB103KEH	MYLAR CAPACITOR	0.01 μ F 50V	C215
GALP3UKA04	WIRES KIT		
RD25TJ102X	CARBON FILM R.	0.25W 1K ohm	R201
RD25TJ271X	CARBON FILM R.	0.25W 270 ohm	R203
RD25TJ393X	CARBON FILM R.	0.25W 39K ohm	R202
RVNA103B06	VR.	10K ohm B-CURVE 16M/M 1-GANG	VR2
RVNA104B02	VR.	100K ohm B-CURVE 16M/M 1-GANG	VR3
RVNA203B03	VR.	20K ohm B-CURVE 16M/M 1-GANG	VR5
RVNA502A06	VR.	5K ohm A-CURVE 16M/M 1-GANG	VR4
RVNB503A04	VR.	50K ohm A-CURVE 16M/M 1-GANG	VR1/S1
SS020220ZL	SLIDE SWITCH		S3/S4/S5/S6/S7
SS020303ZL	SLIDE SWITCH		S2
YJB02S007Z	DC JACK		J2
YJC02S009Z	JACK		J1
YJT03S003Z	3P JACK		J4/J5
YJZ04S008Z	4P MIC JACK		J3
ZMJ2030N06	METER		M
ZPA064139U	LAMP		PL2/PL3
ZQA0770807	SPEAKER		SP
AMRVC24001	FRAME ASSY		1
BRT2635CAX	THIN HEAD RIVET	2.6 x 3.5 ALMINUM	B11-1/B11-2
BSPB2003NN	BIND HEAD SCREW	+ BIT, M2 x 3	B3-1/B3-10/B3-11/B3-12/B3-2/B3-3/B3-4/ B3-5/B3-6/B3-7/B3-8/B3-9
BSPB2606NN	BIND HEAD SCREW	+ BIT, M2.6 x 6	B4-1/B4-2
BSPB3006NN	BIND HEAD SCREW	+ BIT, M3 x 6	B10-1/B10-2/B6/B7-1/B7-2/B8-1/B8-2/ B8-3/B8-4/B9-1/B9-2/B9-3/B9-4
BSPB3008NB	BIND HEAD SCREW	+ BIT, M3 x 8	B5-1/B5-2/B5-3
BSPL3006NB	BIND NAIL SCREW	+ BIT, M3 x 6	B12-1/B12-2/B12-3/B12-4/B12-5/B12-6/B12-7/B12-8
BSPS2605NN	FLAT HEAD SCREW	+ BIT, M2.6 x 5	B1-1/B1-2/B1-3/B1-4/B1-5/B1-6
BTPX3008BZ	I.T BT SCREW	+ BIT, M3 x 8	B2-1/B2-2/B2-3/B2-4
MB762SL008	FRONT PANEL		4
ML121SZ007	BRACKET		11-1/11-2/11-3
ML471SZ002	BRACKET		10
ML522BN001	TERMINAL		14
MS806BN001	TERMINAL		16
MT213BD014	SUPPORT		9
MU243SZ002	BRACKET		8
MU677SZ119	CHASSIS		5
MU773SM102	CASE A		6
MU773SM103	CASE B		7
MVSRVC2401	SER NO PLATE		19
VF176DN002	WASHER		13-1/13-2
VM165RX001	HOLDER		15-1/15-2
VN276SM041	VR KNOB		3-1/3-2/3-3/3-4/3-5
VN286SM019	CH KNOB		2
VS205FB002	SPECER		18
VS605FB001	BARRIER		12-1/12-2
VS706YB006	SHEET		17-1/17-2/17-3/17-4/17-5/17-6
KC000264XX	SCHEMATIC SHEET		
KTRVC240AX	OWNER'S MANUAL		
KF091700E4	POLY BAG		
KF232200E4	POLY BAG		
KF303000E6	POLY BAG		
KKRVC24001	DISPLAY BOX		
ACDC082GEA	DC CORD ASSY		
BTTP4010BN	PAN TAP SCREW	+ BIT, M4 x 10	
BTPT5013AZ	TRUSS TAP SCREW	+ BIT, M5 x 13	
BWG50A06SW	OT LOCK WASHER	OUTSIDE TOOTHED, 5M/M S-ZN	
BWU40855SW	IT LOCK WASHER	INSIDE TOOTHED, 4 M/M S-ZN	
MF284SN001	SCREW		
MU276SW002	HANDLE		
MZ331SZ002	HOLDER		
ZGAAZ501K0	MICROPHONE		
KMRVC24001	MASTER CARTON		

PART NO.	PART NAME	SPECIFICATIONS	SYMBOLIC OR EXPLODED VIEW NO.
VE76JSM127	FRAME		1-A
VS637AK007	FILTER		1-B
BSPB3006NN	BIND HEAD SCREW	+ BIT, M3 x 6	
BSPP3006NT	PAN HEAD SCREW	+ BIT, M3 x 6 PLASTIC	
BSPU3008NN	THIN BIND SCREW	+ BIT, M3 x 8	
CCDB121K0M	CERAMIC CAP.	120 pF 50V	C39
CCDB181K0M	CERAMIC CAP.	180 pF 50V	C45
CCDB220K0M	CERAMIC CAP.	22 pF 50V	C20
CCDB221K0M	CERAMIC CAP.	220 pF 50V	C48/C99
CCDB330KPM	CERAMIC CAP.	33 pF 50V	C23
CCDB390K0M	CERAMIC CAP.	39 pF 50V	C139
CCDB391K0M	CERAMIC CAP.	390 pF 50V	C49
CCDB680K0M	CERAMIC CAP.	68 pF 50V	C37
CCDB820KPM	CERAMIC CAP.	82 pF 50V	C26
CCFB020C0M	CERAMIC CAP.	SL 2 pF 50V	C51/C67
CCFB050CPM	CERAMIC CAP.	PH 5 pF 50V	C121
CCFB050C0M	CERAMIC CAP.	SL 5 pF 50V	C68
CCFB100D0M	CERAMIC CAP.	SL 10 pF 50V	C36
CCFB101K0M	CERAMIC CAP.	100 pF 50V	C46
CCFB121K0M	CERAMIC CAP.	120 pF 50V	C25/C31/C44/C47
CCFB150KPM	CERAMIC CAP.	15 pF 50V	C21
CCFB150K0M	CERAMIC CAP.	15 pF 50V	C80
CCFB151K0M	CERAMIC CAP.	150 pF 50V	C63
CCFB180KPM	CERAMIC CAP.	18 pF 50V	C124
CCFB180K0M	CERAMIC CAP.	18 pF 50V	C19
CCFB220K0M	CERAMIC CAP.	22 pF 50V	C62
CCFB221K0M	CERAMIC CAP.	220 pF 50V	C103
CCFB270K0M	CERAMIC CAP.	27 pF 50V	C54
CCFB271K0M	CERAMIC CAP.	270 pF 50V	C50
CCFB390K0M	CERAMIC CAP.	39 pF 50V	C8
CCFB391K0M	CERAMIC CAP.	390 pF 50V	C41
CCFB470KPM	CERAMIC CAP.	47 pF 50V	C123
CCFB470K0M	CERAMIC CAP.	47 pF 50V	C56
CCFB560KPM	CERAMIC CAP.	56 pF 50V	C1
CEAB330ALX	ELYT. CAPACITOR	33 μF 6.3V	C100
CEAC101ALX	ELYT. CAPACITOR	100 μF 10V	C78
CEAC330ALX	ELYT. CAPACITOR	33 μF 10V	C140
CEAC470ALX	ELYT. CAPACITOR	47 μF 10V	C82
CEAD100ALX	ELYT. CAPACITOR	10 μF 16V	C109/C79
CEAD101ALX	ELYT. CAPACITOR	100 μF 16V	C94
CEAD221ALX	ELYT. CAPACITOR	220 μF 16V	C105/C122
CEAD470ALX	ELYT. CAPACITOR	47 μF 16V	C128
CEAE3R3ALX	ELYT. CAPACITOR	3.3 μF 25V	C108/C134
CEAE4R7ALX	ELYT. CAPACITOR	4.7 μF 25V	C88
CEAE470ZLS	ELYT. CAPACITOR	47 μF 25V SP	C11
CEAG010ZMN	ELYT. CAPACITOR	1 μF 50V MS	C4
CEED102ALX	ELYT. CAPACITOR	1000 μF 16V	C110
CEVC330ALX	ELYT. CAPACITOR		C106
CEVD470ALX	ELYT. CAPACITOR		C102
CEVE3R3ALX	ELYT. CAPACITOR		C107
CEVG010ALX	ELYT. CAPACITOR		C53
CKDB103PEM	CERAMIC CAP.	0.01 μF 50V	C111/C135/C22/C33/C35/C5/C66/C77
CKDB222PEM	CERAMIC CAP.	2200 pF 50V	C126/C97
CKDB223ZFM	CERAMIC CAP.	0.022 μF 50V	C70
CKDB331KBM	CERAMIC CAP.		C24
CKDB472PEM	CERAMIC CAP.	4700 pF 50V	C52
CKDB473ZFM	CERAMIC CAP.	0.047 μF 50V	C130/C136/C138/C59/C6/C74/C9
CKDB561KBM	CERAMIC CAP.	560 pF 50V	C92
CKFB102PEM	CERAMIC CAP.	1000 pF 50V	C93
CKFB103PEM	CERAMIC CAP.	0.01 μF 50V	C10/C112/C127/C30/C32/C38/C42/C43/C55/ C58
CKFB222PEM	CERAMIC CAP.	2200 pF 50V	C125
CKFB472PEM	CERAMIC CAP.	4700 pF 50V	C90
CKFB473ZFM	CERAMIC CAP.	0.047 μF 50V	C60/C65
CQMB102KEH	MYLAR CAPACITOR	1000 pF 50V	C85
CQMB102KTH	MYLAR CAPACITOR	1000 pF 50V	C86
CQMB103KEH	MYLAR CAPACITOR	0.01 μF 50V	C72/C91
CQMB103KTH	MYLAR CAPACITOR	0.01 μF 50V	C75/C76/C96
CQMB182KEH	MYLAR CAPACITOR	1800 pF 50V	C119
CQMB223KEH	MYLAR CAPACITOR	0.022 μF 50V	C87
CQMB223KTH	MYLAR CAPACITOR	0.022 μF 50V	C120/C83
CQMB272KEH	MYLAR CAPACITOR	2700 pF 50V	C116
CQMB333KEH	MYLAR CAPACITOR	0.033 μF 50V	C115
CQMB333KTH	MYLAR CAPACITOR	0.033 μF 50V	C118

PART NO.	PART NAME	SPECIFICATIONS	SYMBOLIC OR EXPLODED VIEW NO.
CQMB473KEH	MYLAR CAPACITOR	0.047 μ F 50V	C113/C40/C7/C89
CQMB473KTH	MYLAR CAPACITOR	0.047 μ F 50V	C71/C73/C81/C84
CQMB682KEH	MYLAR CAPACITOR	6800 pF 50V	C114
CQMB683KEH	MYLAR CAPACITOR	0.068 μ F 50V	C101/C104
CSSE3R3MDC	TANTALUM CAP.	3.3 μ F 25V	C98
CTZ6200H01	TRIMMER CAP.		CT-1/CT-2
FBR455A24P	CERAMIC FILTER		CF2
FB10R7A01M	CERAMIC FILTER		CF1
LA1JG1010A	CHOKO COIL		L10
LA1KE1011A	RF COIL		L6
LA1KE1211A	RF COIL		L11
LDADB4024B	RF COIL		L14/L15
LDADX3825M	RF COIL		L7
LF124KC01S	RF COIL		L16
LF2R2KD01N	RF COIL		L3
LF270KD01N	RF COIL	27 μ H	L1
LF680KD01N	RF COIL		L12/L5
LJ119H001Y	CHOKO COIL		CH-1
MB644SX002	SHIELD CASE		
ML454AD001	HEAT SINK		
MS327AD004	HEAT SINK		
MU453AD001	HEAT SINK		
MW401CX001	SHORT JUMPER	JW-10	
MW401CX003	SHORT JUMPER		
MW401CX004	SHORT JUMPER	JW-5	
PTBM134A0X	PRINTED W. BOARD		
QDCTT410XQ	VARI-CAP. DIODE	1TT410 12V NO-RANK 26MIN	D13/D3
QDG0A90XXN	GERMANIUM DIODE	0A90 NO-RANK	D11/D12/D6/D7
QDSMA150XN	SILICON DIODE	MA150 VF 1.2V VR 35V NO-RANK 24MIN	D14/D16/D17/D4/D5/D9
QDSSR1K4AP	SILICON DIODE	SR1K4LF VR 200 A-RANK 9MIN	D10
QDZA1062MN	ZENER DIODE	MA1062M	D2
QDZA1091MN	ZENER DIODE	MA1091M	D8
QQMAN240PN	I.C.	AN240P	IC3
QQM06458AC	I.C.	LA6458	IC5
QQM07205ET	I.C.	TA7205	IC4
QQ007137AC	I.C.	LC7137	IC1
QTAJA100BQ	TRANSISTOR	JA100 PORQ-RANK	Q15
QTA0719XHN	TRANSISTOR	2SA719 P,Q,R-RANK	Q17
QTCJC500BQ	TRANSISTOR	JC500 P,Q-RANK	Q12/Q14/Q2
QTCJC500DQ	TRANSISTOR	JC500 O,P,Q-RANK	Q18/Q19/Q20/Q21/Q22/Q23
QTC1318XDN	TRANSISTOR	2SC1318 Q,R-RANK	Q16
QTC1327XBN	TRANSISTOR	2SC1327 T-RANK	Q13
QTC1359XBN	TRANSISTOR	2SC1359 B,C-RANK	Q10
QTC1846XAN	TRANSISTOR	2SC1846 Q,R,S-RANK	Q5
QTC1909XBA	TRANSISTOR	2SC1909 Q,R-RANK	Q6
QTC2724XDE	TRANSISTOR	2SC2724 D-RANK	Q1
QTC2724XFE	TRANSISTOR	2SC2724 C,D-RANK	Q11/Q25/Q3/Q4/Q7/Q8/Q9
RD25PJ101X	CARBON FILM R.	0.25W 100 ohm	R22/R28
RD25PJ102X	CARBON FILM R.	0.25W 1K ohm	R24/R36/R37/R68/R70/R91
RD25PJ103X	CARBON FILM R.	0.25W 10K ohm	R2/R4/R60/R65/R66/R72/R74/R75/ R78/R79/R85/R90/R94
RD25PJ104X	CARBON FILM R.	0.25W 100K ohm	R48
RD25PJ121X	CARBON FILM R.	0.25W 120 ohm	R35
RD25PJ153X	CARBON FILM R.	0.25W 15K ohm	R42/R67/R84
RD25PJ154X	CARBON FILM R.	0.25W 150K ohm	R15/R8
RD25PJ182X	CARBON FILM R.	0.25W 1.8K ohm	R61
RD25PJ183X	CARBON FILM R.	0.25W 18K ohm	R63/R82
RD25PJ221X	CARBON FILM R.	0.25W 220 ohm	R21
RD25PJ222X	CARBON FILM R.	0.25W 2.2K ohm	R54/R58/R81/R93
RD25PJ223X	CARBON FILM R.	0.25W 22K ohm	R11/R46/R62
RD25PJ224X	CARBON FILM R.	0.25W 220K ohm	R9
RD25PJ271X	CARBON FILM R.	0.25W 270 ohm	R119/R87
RD25PJ272X	CARBON FILM R.	0.25W 2.7K ohm	R10/R29/R69
RD25PJ273X	CARBON FILM R.	0.25W 27K ohm	R52/R73
RD25PJ331X	CARBON FILM R.	0.25W 330 ohm	R20/R44/R50
RD25PJ332X	CARBON FILM R.	0.25W 3.3K ohm	R13/R34/R41/R89
RD25PJ333X	CARBON FILM R.	0.25W 33K ohm	R43
RD25PJ391X	CARBON FILM R.	0.25W 390 ohm	R16/R33/R88
RD25PJ393X	CARBON FILM R.	0.25W 39K ohm	R80
RD25PJ470X	CARBON FILM R.	0.25W 47 ohm	R45/R64
RD25PJ471X	CARBON FILM R.	0.25W 470 ohm	R31/R39
RD25PJ472X	CARBON FILM R.	0.25W 4.7K ohm	R18/R38/R53/R6/R83/R92
RD25PJ473X	CARBON FILM R.	0.25W 47K ohm	R12/R23/R26/R49

PART NO.	PART NAME	SPECIFICATIONS	SYMBOLIC OR EXPLODED VIEW NO.
RD25PJ474X	CARBON FILM R.	0.25W 470K ohm	R76/R77
RD25PJ560X	CARBON FILM R.	0.25W 56 ohm	R5
RD25PJ561X	CARBON FILM R.	0.25W 560 ohm	R1/R57
RD25PJ562X	CARBON FILM R.	0.25W 5.6K ohm	R3/R51/R122
RD25PJ680X	CARBON FILM R.	0.25W 68 ohm	R19
RD25PJ681X	CARBON FILM R.	0.25W 680 ohm	R25/R27/R30/R40
RD25PJ682X	CARBON FILM R.	0.25W 6.8K ohm	R17
RD25PJ820X	CARBON FILM R.	0.25W 82 ohm	R59
RD25PJ821X	CARBON FILM R.	0.25W 820 ohm	R47/R7
RD25PJ824X	CARBON FILM R.	0.25W 820K ohm	R56
RD25TJ472X	CARBON FILM R.	0.25W 4.7K ohm	R55
RD25TJ682X	CARBON FILM R.	0.25W 6.8K ohm	R14
RD25T0000X	CARBON FILM R.	0-OHM STRAITE	
RGHANJ271B	M-OXIDE FILM R.	1/2W 270 ohm	R103/R96
RG1ANJ151B	M-OXIDE FILM R.	1W 150 ohm	R102
RPDNB50104	SUB-MINI VR.		RV6
RPGNB20201	SEMI-FIXED VR.	2K ohm B-CURVE	RV2
RPGNB20301	SEMI-FIXED VR.	20K ohm B-CURVE	RV1/RV3/RV4
RPGNB30101	SEMI-FIXED VR.	300 ohm B-CURVE	RV5
RXHANJ100B	M-OXIDE FILM R.	1/2W 10 ohm	R86
RX1ANJ4R7B	M-OXIDE FILM R.	1W 4.7 ohm	R97
SR2040203H	ROTARY SWITCH		SW-1
TRA5CZ001M	RF COIL		L4
TRA5CZ002M	RF COIL		L8
TRA5CZ003M	RF COIL		L9
TR07LA004N	I.F.T.		T10
TR07LA023N	I.F.T.		T11/T12
TR07MA006N	RF COIL		T9
TR10CA006T	RF COIL		T3
TR10CB003T	R.F.T.		T2
TR10CM003M	RF COIL		T7
TR10CP005S	RF TRANS		T4
TR10DB003M	RF COIL		T1
TR10MA018M	RF COIL		T8
TR10MP003T	RF COIL		T5
VS223RH002	SILICON SHEET		
VS311XX001	BARRIER		
WUG007EEXX	HI-WRAP WIRE		N04
WUG013EEXX	HI-WRAP WIRE		N08
WUG116EEXX	HI-WRAP WIRE		N01
WUG218EEXX	HI-WRAP WIRE		N02
WUG313EEXX	HI-WRAP WIRE		N03
WUG417EEXX	HI-WRAP WIRE		N09
WUG611EEXX	HI-WRAP WIRE		N06
WUG913EEXX	HI-WRAP WIRE		N010
WUH004AAXX	HI-WRAP WIRE		N017
XAS1C2006X	XTAL OCILLATOR		X1
YFL0000001	FERRITE CORD		
MW401CX001	SHORT JUMPER	JW-10	
PTLD010C0X	PRINTED W. BOARD		
QL•SL2221C	L.E.D.	SL2221C GREEN COM.-A.	LED
ZZZ0000020	PC JOINT		
CKDB103PEM	CERAMIC CAP	0.01μF 50V -0, +100% E	C251
MW401CX004	SHORT JUMPER	JW-5	J2
PTSW154A0X	PRINTED W. BOARD		
QDSMA150XN	SILICON DIODE	MA150 VF 1.2V VR 35V NO-RANK 24MIN	D251/D252/D253/D254/D255/D256/ D257/D258/D259/D260/D261/D262
QTC1383XAN	TRANSISTOR	2SC1383 Q-RANK	Q251
RD25TJ102X	CARBON FILM R	0.25W 1K ohm	R251/R252/R253/R254/R255/R256/ R257/R258/R259/R260/R261/R262/ R263/R264
RD25TJ223X	CARBON FILM R.	0.25W 22K ohm	R265