



Figure 21 WIRING SIDE BOARD (P.W.B. NO. F0485AF-4)

NOTE:

- 1) In case of adding ceramic filter CF-2 and CF-3. (Reference figures are 20 and 21.)
 - ① Add a ceramic filter CF-2 (RFILA0050AFZZ)
 - ② Add a ceramic filter CF-3 (RFILA0001AFZZ)
 - ③ Change the capacitor C37 from 0.01MFD to 680PF (VCCSPU1HL681J)
 - ④ Cut the printed circuit pattern, the place is shown on Figure 21-①.
- 2) In case of adding ceramic filter CF-3. (Reference figures are 20 and 21)
 - ① Add a ceramic filter CF-3 (RFILA0001AFZZ)
 - ② Change the capacitor C37 from 0.01MFD to 680PF (VCCSPU1HL681J)