

This Information Is Provided By  
***CBTricks.com***

**Whistler 900 Parts List**

**Liability of damages to any equipment is the sole responsibility of the user! Downloading, viewing, or using any information provided on these pages automatically accepts the user to the terms of this agreement!**

**Modifications are provided for information purposes only!**

Supporters of CBTricks.com paid for the hosting so you would have this file.

CBTricks.com is a non-commercial personal website was created to help promote the exchange of service, modification, technically oriented information, and historical information aimed at the Citizens Band, GMRS (CB "A" Band), MURS, Amateur Radios and RF Amps.

CBTricks.com is not sponsored by or connected to any Retailer, Radio, Antenna Manufacturer or Amp Manufacturer, or affiliated with any site links shown in the links database. The use of product or company names on my web site is not endorsement of that product or company.

The site is supported with donations from users, friends and selling of the Site Supporters DVD's to cover some of the costs of having this website on the Internet instead of relying on banner ads, pop-up ads, commercial links, etc. Thus I do not accept advertising banners or pop-up/pop-under advertising or other marketing/sales links or gimmicks on my website.

ALL the money from donations is used for CBTricks.com I didn't do all the work to make money (I have a day job). This work was not done for someone else to make money also, for example the ebay CD sellers.

All Trademarks, Logos, and Brand Names are the property of their respective owners.

This information is not provided by, or affiliated in any way with any radio or antenna Manufacturers.

**Thank you for any support you can give.**

For information on how to Support CBTricks.com

<http://www.cbtricks.com/support/>

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.
	244-003-7	Diode GE OA90	10,000	D106, 112, 203, 211, 419, 420, 421, 422, 501, 502
	245-004-3	Diode SI 1N4002	2,000	D306, 423
	260-003-3	Crystal 10.240 MHz HC-18/U	2,000	X1, 2
	270-007-0	Ceramic Filter CFW455HT	2,000	CF102, 202
	270-010-2	Ceramic Filter 10.7MJ	2,000	CF101, 201
	300-024-5	Transformer OPT	1,000	T1
	300-045-4	Transformer Choke	1,000	CH1
	310-022-6	Coil RF Choke 10UH Core	2,000	RFC413, 414
	310-025-9	Coil Choke 1UH Bobbin	1,000	RFC406
	310-027-1	Coil RE Choke 1UH Spring	3,000	RFC306, 307, 308
	310-038-1	Coil RF Choke 22UH Bobbin	2,000	RFC309, 415
	310-065-5	Coil RF Choke 0.5UH Spring	1,000	RFC409
	310-069-9	Coil RF Choke 6.8UH PC	3,000	RFC301, 303, 408
	310-100-3	Coil Choke 4UH Bobbin Type	2,000	RFC302, 401
	320-032-8	Coil AM TX Ant 27 MHz A	1,000	L412
	320-033-9	Coil AM TX Ant 27 MHz B	1,000	L410
	320-034-0	Coil AM IFT 27 MHz TX Ant Tuning C	1,000	L411
	320-317-6	Coil VCO	2,000	L303, 402
	320-318-7	27 MHz RF PRE AMP A (TX)	4,000	L304, 305, 403, 404
	320-320-8	27 MHz RF-C (TX)	1,000	L407
	320-380-2	27 MHz RX Ant A	2,000	L101, 201
	320-385-7	10.7 MHz Mixer B	2,000	L105, 205
	320-386-8	455 KHz A	2,000	L106, 206
	320-387-9	455 KHz B	2,000	L107, 207
	320-388-0	455 KHz DET	2,000	L108, 208
	320-400-7	10.7 MHz Mixer A	2,000	L103, 203
	320-407-4	RX AMP 10.7 MHz	2,000	L104, 204
	320-408-5	RX Ant Tunig 27 MHz	1,000	L405
	320-421-6	RX Ant 27 MHz	2,000	L102, 202
	4A1-005-A	Main B'D P.C.B Ass'y	1,000	
	401-088-A	P.C.B Main 205 × 174 × 1.6t	1,000	
	401-287-A	P.C.B Selector SW 35 × 13 × 1.6t 1/0	1,000	
	401-288-A	P.C.B 9/19 SW 28 × 21 × 1.6t	1,000	
	401-394-A	P.C.B LED Display 55 × 18 × 1.6t	1,000	
	401-921-B	P.C.B SWR 41 × 35 × 1.6t	1,000	
	420-605-7	Relay MZ-12HS	1,000	RLY-1
	770-336	Shield Plate SPTE-N 90 × 25 × 0.3t	2,000	
	771-280	Shield Plate SPTE-N 0.3t	1,000	
	771-285	Shield Plate SPTE-N 0.3t	1,000	
	902-050	Insulation Plate Fiber 26 × 14 × 0.3t	2,000	
4	510-57P-A	Packing Ass'y	1,000	
	510-57M-A	MIC Ass'y	1,000	
	420-210-3	Electronic Components Unit HDR7105-01-010	1,000	
	420-319-9	3 Cond 1SH CB Curl Cord KSK-23019 BLK (Matte)	1,000	
	421-038-0	Connector Plug SW-1461	1,000	
	432-034-1	Push SW HPW0208 01 010	1,000	
	504-292	Power Cord Ass'y	1,000	
	600-060	Securing Screw M6 (P = 1) × 12	2,000	
	623-025	(+) Tapping Screw (P.H) 3 × 5-2S BLK	1,000	
	624-066	(+) Tapping Screw (R.H) 4 × 10-2S Zn-Plate	2,000	
	625-007	(+) Tapping Screw (T.H) 5 × 12-1S Zn Plate	3,000	
	664-411	Washer (Lock "B" Type) M4 Zn-Plate	2,000	
	664-518	Washer (Lock "B" Type) M5 Zn-Plate	3,000	
	693-160	(+) Plus Screw (P.H) 3 × 18 Ni-Plate	1,000	
	693-170	(+) Plus Screw (P.H) 3 × 20 Ni-Plate	2,000	
	716-995	Bottom Cover ABS 94HB Dark (Charcoal) "S"	1,000	
	717-000	Upper Cover ABS 94HB Dark (Charcoal) "S"	1,000	

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.
	131-202-1	Capacitor Ceramic 120PF 50WV	3,000	C316, 338, 423
	131-801-2	Capacitor Ceramic 18PF 50WV	2,000	C309, 416
	132-003-3	Capacitor Ceramic 2PF 50WV	2,000	C124, 230
	132-201-5	Capacitor Ceramic 22PF 50WV SL	4,000	C304, 310, 404, 417
	132-204-8	Capacitor Ceramic 220PF 50WV	4,000	C315, 342, 422, 438
	132-705-4	Capacitor Ceramic 27PF 50WV (NPO) $\phi$ 5D	2,000	C311, 420
	133-001-6	Capacitor Ceramic 3PF 50WV	4,000	C112, 120, 212, 226
	133-301-7	Capacitor Ceramic 33PF 50WV	2,000	C313, 421
	133-302-8	Capacitor Ceramic 330PF 50WV SL	2,000	C435, 439
	133-501-1	Capacitor Ceramic 35PF 50WV	2,000	C101, 201
	133-901-9	Capacitor Ceramic 39PF 50WV	2,000	C319, 426
	134-003-3	Capacitor Ceramic 4PF 50WV	2,000	C322, 427
	134-701-0	Capacitor Ceramic 47PF 50WV	2,000	C118, 217
	136-001-1	Capacitor Ceramic 6PF 50WV	2,000	C116, 215
	136-002-2	Capacitor Ceramic 60PF (NPO) 50WV	1,000	C436
	136-003-3	Capacitor Ceramic 60PF 50WV	2,000	C323, 431
	161-005-9	Capacitor Mica 100PF 50WV	1,000	C443
	161-803-3	Capacitor Mica 180PF 50WV	1,000	C446
	162-702-0	Capacitor Mica 270PF 50WV	1,000	C444
	163-303-8	Capacitor Mica 330PF 50WV	1,000	C445
	163-501-0	Capacitor Mica 35PF 50WV	4,000	C301, 312, 409, 415
	163-901-8	Capacitor Mica 39PF 50WV	2,000	C302, 410
	164-701-9	Capacitor Mica 47PF 50WV	2,000	C442, 501
	168-201-4	Capacitor Mica 82PF 50WV	1,000	C433
	172-002-4	Capacitor Trimmer 20PF TZ03R200E	2,000	CT1, 2
	191-001-4	M.P Capacitor 0.01 $\mu$ F 50WV +5%:J	7,000	C15, 16, 127, 129, 235, 333, 511
	191-002-5	M.P Capacitor 0.001 $\mu$ F 50WV +5%:J	5,000	C325, 326, 503, 4, 5
	191-003-6	M.P Capacitor 0.1 $\mu$ F 50WV +10%:K	1,000	C340
	192-201-3	M.P Capacitor 0.0022 $\mu$ F 50WV +5%:J	7,000	C220, 221, 222, 224, 330, 332, 334
	192-203-5	M.P Capacitor 0.022 $\mu$ F 50WV +5% "J"	2,000	C130, 236
	193-302-6	M.P Capacitor 0.033 $\mu$ F 50WV +10%:K	1,000	C506
	194-701-8	M.P Capacitor 0.0047 $\mu$ F 50WV +5%:J	3,000	C128, 233, 508
	194-703-0	M.P Capacitor 0.047 $\mu$ F 50WV +10%:K	10,000	C121, 5, 6, 227, 231, 232, 303, 328, 9, 406
	196-802-6	M.P Capacitor 0.0068 $\mu$ F 50WV +5%:J	1,000	C331
	196-803-7	M.P Capacitor 0.068 $\mu$ F 50WV +10%:K	5,000	C305, 307, 405, 407, 605
	202-044-2	Transistor KTC K161 (Y)	3,000	Q106, 205, 502
	203-002-9	Transistor MPS9634 (C)	15,000	Q109, 206, 210, 211, 212, 213, 214, 215, 216, 305, 406, 8, 410, 9, 420
	203-005-2	Transistor MPS9426 (C)	14,000	Q102, 3, 201, 2, 301, 2, 3, 405, 7, 9, 411, 16, 17, 501
	203-009-6	Transistor MPS9681 (T)	6,000	Q306, 7, 403, 412, 418, 503
	203-010-6	Transistor MPS9418 (T)	5,000	Q101, 308, 401, 404, 414
	203-011-7	Transistor MPS9623 (H)	2,000	Q107, 207
	203-012-8	Transistor MPS9623 (I)	2,000	Q108, 208
	203-014-0	Transistor MPS9631 (T)	3,000	Q209, 304, 402
	209-016-2	FET BF964 (A)	4,000	Q104, 5, 203, 4
	223-080-5	IC MC14066B	2,000	IC3, 4
	224-036-1	IC LB1407	1,000	IC6
	241-020-7	Diode Zener UZ9.1B	1,000	D411
	242-002-6	Diode Varicap MV2209	2,000	D301, 413
	243-004-3	Diode SI 1S2473	52,000	D101-5, 7, 8, 9, 10, 1, 3 4, 5, 6, 201, 2, 4, 5, 6, 7, 8, 10, 12, 13, 14, 401, 402, 403, 404, 405, 406, 407, 408, 601

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.
	002-334-2	Resistor Carbonfilm 330K ohm 1/16W +5% "S"	2,000	R145, 149
	002-391-3	Resistor Carbonfilm 390 ohm 1/16W +5% "S"	4,000	R202, 336, 439, 451
	002-392-4	Resistor Carbonfilm 3.9K ohm 1/16W +5% "S"	6,000	R118, 136, 214, 245, 256, 261
	002-394-6	Resistor Carbonfilm 390K ohm 1/16W +5% "S"	1,000	R230
	002-470-1	Resistor Carbonfilm 47 ohm 1/16W +2%	4,000	R329, 358, 438, 458
	002-471-2	Resistor Carbonfilm 470 ohm 1/16W +5% "S"	15,000	R115, 120, 2, 6, 9, 132, 212, 7, 9, 25, 238, 41, 342, 426, 430
	002-472-3	Resistor Carbonfilm 4.7K ohm 1/16W +5% "S"	17,000	R131, 48, 240, 326, 334, 7, 357, 72, 3, 7, 428, 435, 449, 453, 6, 7, 505
	002-473-4	Resistor Carbonfilm 47K ohm 1/16W +5% "S"	5,000	R138, 141, 247, 250, 454
	002-474-5	Resistor Carbonfilm 470K ohm 1/16W +5% "S"	2,000	R349, 504
	002-561-0	Resistor Carbonfilm 560 ohm 1/16W +5% "S"	4,000	R114, 209, 472, 477
	002-562-1	Resistor Carbonfilm 5.6K ohm 1/16W +5% "S"	3,000	R221, 506, 507
	002-563-2	Resistor Carbonfilm 56K ohm 1/16W +5% "S"	2,000	R144, 483
	002-680-4	Resistor Carbonfilm 68 ohm 1/16W +5% "S"	2,000	R352, 467
	002-683-7	Resistor Carbonfilm 68K ohm 1/16W +5% "S"	4,000	R128, 140, 237, 249
	002-821-5	Resistor Carbonfilm 820 ohm 1/16W +5% "S"	4,000	R330, 353, 442, 482
	002-822-6	Resistor Carbonfilm 8.2K ohm 1/16W +5% "S"	4,000	R344, 345, 356, 455
	002-824-8	Resistor Carbonfilm 820K ohm 1/16W +5% "S"	1,000	R340
	012-391-6	Resistor Carbonfilm 390 ohm 1/2W +5% "S"	1,000	R416
	012-472-6	Resistor Carbonfilm 4.7K ohm 1/2W +5% "S"	1,000	R470
	018-100-0	Resistor Metaloxide 10 ohm 1W "S"	1,000	R465
	018-181-3	Resistor Metaloxide 180 ohm 1W	1,000	R400
	019-150-0	Resistor Metaloxide 15 ohm 2W "S"	1,000	R374
	019-221-1	Resistor Metaloxide 220 ohm 2W +5%	1,000	R375
	061-103-3	Resistor Semifixed 10K ohm 8 Dia "H"	4,000	RV101, 102, 201, 202
	061-202-9	Resistor Semifixed 2K ohm 8 Dia "H"	1,000	RV301
	061-204-1	Resistor Semifixed 200K ohm 8 Dia "H"	1,000	RV402
	061-502-0	Resistor Semifixed 5K ohm 8 Dia "H"	1,000	RV401
	100-405-4	Capacitor Elect 0.47μF 50WV (5 × 11)	2,000	C343, 510
	101-006-2	Capacitor Elect 1.0μF 50WV (5 Dia × 11)	3,000	C324, 429, 349
	101-012-7	Capacitor Elect 10μF 16WV (5 Dia × 11)	11,000	C102, 109, 203, 209, 240, 241, 314, 337, 348, 412, 509
	101-022-6	Capacitor Elect 100μF 16WV (8 Dia × 11.5)	3,000	C238, 239, 345
	101-048-0	Capacitor Elect 1000μF 16WV SR (12.5 Dia × 16.5)	1,000	C344
	102-207-2	Capacitor Elect 2.2μF 50WV (5 Dia × 11)	5,000	C129, 234, 320, 430, 448
	102-223-6	Capacitor Elect 220μF 16WV (10 Dia × 12.5)	1,000	C403
	102-232-4	Capacitor Elect 2200μF 16WV (16 × 25)	2,000	C347, 453
	103-308-5	Capacitor Elect 3.3μF 50WV (5Dia × 11)	3,000	C200, 225, 604
	103-313-9	Capacitor Elect 33μF 16WV (5 Dia × 11)	6,000	C110, 114, 211, 308, 339, 411
	104-707-7	Capacitor Elect 4.7μF 50WV (5 Dia × 11)	3,000	C131, 237, 350
	104-712-1	Capacitor Elect 47μF 16WV (6 Dia × 11)	5,000	C327, 336, 341, 352, 460
	124-701-7	Capacitor Poly 470PF 50WV	2,000	C132, 250
	130-101-8	Capacitor Ceramic 0.001μF 50WV	3,000	C346, 351, 353
	130-102-9	Capacitor Ceramic 0.01μF 50WV (HIK (B))	40,000	C13, 14, 103, 4, 6, 8, 11, 3, 5, 202, 4, 6, 8, 10, 3, 4, 318, 21, 401, 2, 13, 4, 8
	130-402-0	Capacitor Ceramic 0.0047μF 50WV	2,000	C317, 424
	130-405-3	Capacitor Ceramic 0.047μF 50WV	26,000	C4, 5, 6, 7, 8, 9, 10, 11, 12, 105, 17, 19 22, 3, 205, 16, 18, 28, 9, 306, 35, 408, 34, 41, 49, 51
	131-012-6	Capacitor Ceramic 100PF SLφ5D	1,000	C133
	131-016-0	Capacitor Ceramic 1PF 50WV SL φ4D	2,000	C107, 207

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.
	450-602-3	Resistor Variable (VR) 50KA (W/OFF-ON SW)	1,000	VR1
	611-086	(+) Machine Screw (F.H) M2.6 × 4 Zn-Plate	4,000	FRONT BODY + 3P3C SWITCH
	613-156	(+) Machine Screw (F.H) M3 × 4 Zn-Plate	2,000	
	613-253	(+) Machine Screw (B.H) M3 × 4 Zn-Plate	4,000	MAIN BODY + FRONT BODY
	613-332	(+) Machine Screw (B.H) M3 × 10 Zn-Plate	5,000	POWER CORD:3 IC, TR:2
	623-335	(+) Tapping Screw (B.H) 3 × 8-2S Zn-Plate	4,000	MAIN PCB + MAIN BODY
	651-024	Nut SS41 M3-1S Zn-Plate	5,000	
	660-572	Washer Flat Fiber φ3.2 × φ8 × 1.2t	1,000	
	670-025	Rivet Blind ALB	2,000	NAME PLATE + MAIN BODY
	701-880	Main Body SPC	1,000	
	701-890	Front Body SPC	1,000	
	730-343	Holder (ANT MTG) SPC Ni-P 42 × 40 × 0.5t	1,000	
	760-704	Heat Sink (IC MTG) Alp 30 × 18 × 2t	10,000	
	770-390	Shield Plate SPTe 26 × 17 × 0.3t	2,000	
	793-572	Name Plate (Whistler-900) Alp3 70 × 18 × 0.5t	1,000	
	905-395	Insulation Plate Fiber 19 × 11 × 0.3t	2,000	
	992-440	Ant Receptacle (W/Nut Washer) Kyeong Seovg M Type 8112	1,000	
3	510-57M-P	Main PCB Ass'y	1,000	
	001-913-0	Resistor Carbonfilm 91K ohm 1/16W + 5% "F"	1,000	R363
	002-101-8	Resistor Carbonfilm 100 ohm 1/16W + 5% "S"	8,000	R112, 119, 210, 216, 429, 464, 473, 510
	002-102-9	Resistor Carbonfilm 1K ohm ohm 1/16W + 5% "S"	59,000	R106, 9, 23-5, 7, 130, 203, 6, 20, 36, 9, 22-4, 259, 60, 365, 6, 7, 8, 76, 604
	002-103-0	Resistor Carbonfilm 10K ohm 1/16W + 5% "S"	28,000	R108, 16, 46, 205, 13, 34, 52, 53, 54, 63, 64, 323, 55, 62, 99, 425, 27, 32
	002-104-1	Resistor Carbonfilm 100K ohm 1/16W + 5% "S"	18,000	R113, 7, 142, 211, 5, 33, 35, 62, 65, 327, 43, 436, 52, 501, 8, 332, 602, 3
	002-105-2	Resistor Carbonfilm 1M ohm 1/16W + 5% "S"	2,000	R228, 509
	002-121-6	Resistor Carbonfilm 120 ohm 1/16W + 5% "S"	1,000	R474
	002-122-7	Resistor Carbonfilm 1.2K ohm 1/16W + 5% "S"	2,000	R361, 469
	002-124-9	Resistor Carbonfilm 120K ohm 1/16W + 5% "S"	1,000	R601
	002-151-3	Resistor Carbonfilm 150 ohm 1/16W + 5% "S"	3,000	R359, 475, 476
	002-152-4	Resistor Carbonfilm 1.5K ohm 1/16W + 5% "S"	4,000	R101, 102, 338, 461
	002-153-5	Resistor Carbonfilm 15K ohm 1/16W + 5% "S"	4,000	R143, 147, 258, 364
	002-154-6	Resistor Carbonfilm 150K ohm 1/16W + 5% "S"	4,000	R139, 248, 335, 450
	002-182-1	Resistor Carbonfilm 1.8K ohm 1/16W + 5% "S"	2,000	R269, 271
	002-183-2	Resistor Carbonfilm 18K ohm 1/16W + 5% "S"	20,000	R226, 227, 229, 315, 316, 317, 318, 319, 320, 321, 322, 347, 417, 418, 419, 420, 421, 422, 423, 424
	002-220-2	Resistor Carbonfilm 22 ohm 1/16W + 5% "S"	3,000	R328, 431, 437
	002-222-4	Resistor Carbonfilm 2.2K ohm 1/16W + 5% "S"	11,000	R103, 231, 325, 331, 348, 351, 401, 434, 444, 462, 463
	002-223-5	Resistor Carbonfilm 22K ohm 1/16W + 5% "S"	5,000	R134, 135, 243, 244, 350
	002-224-6	Resistor Carbonfilm 220K ohm 1/16W + 5% "S"	1,000	R448
	002-225-7	Resistor Carbonfilm 2.2M ohm 1/16W + 5% "S"	2,000	R268, 270
	002-229-1	Resistor Carbonfilm 2.2 ohm 1/16W + 5% "S"	1,000	R468
	002-272-9	Resistor Carbonfilm 2.7K ohm 1/16W + 5% "S"	9,000	R104, 107, 121, 204, 218, 266, 7, 333, 447
	002-273-0	Resistor Carbonfilm 27K ohm 1/16W + 5% "S"	4,000	R111, 208, 232, 251
	002-331-9	Resistor Carbonfilm 330 ohm 1/16W + 5% "S"	5,000	R105, 133, 201, 242, 354
	002-332-0	Resistor Carbonfilm 3.3K ohm 1/16W + 5% "S"	6,000	R110, 207, 255, 257, 341, 6
	002-333-1	Resistor Carbonfilm 33K ohm 1/16W + 5% "S"	5,000	R137, 246, 324, 433, 478

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.	
1	510-57C-A	Cover Ass'y	1,000		
	420-102-9	Speaker 3" 8 ohm 2W	1,000		
	613-156	(+) Machine Screw (F.H) M3×4 Zn-Plate	4,000	ESC + FRONT	
	621-025	(+) Tapping Screw (P.H) 2.6×6-1S Zn-Plate	2,000	ESC + LED PCB	
	623-405	(+) Tapping Screw (B.H) 3×10-2S BLK	3,000	SPK + HOLDER	
	633-082	(+) Tap Tite Screw (B.H) 3×6 BLK	8,000	MAIN BODY + U.B COVER	
	660-138	Washer Rubber 7×1.5 BLK	2,000	TR + MAIN BODY	
	717-035	Bottom Cover SPC210×183.6×40.5	1,000		
	717-040	Upper Cover SPC210×183.6×40.5	1,000		
	730-015	Holder (Speaker) SPC25×25×1t	3,000	SPEAKER COVER	
	801-105	Escutcheon ABS 94HB Dark Harcoal	1,000		
	813-380	Lens (Smoke) Alryl 53×25	1,000		
	813-390	Lens (Clear) P.C 24×10	1,000		
	813-405	Lens (Lighting) Acryl Clear	1,000		
	824-815	Knob (Channel) ABS 94HB Dark Charcoal	3,000		
	824-830	Knob (Control) ABS 94HB Dark Charcoal	5,000		
	824-840	Knob (Push) ABS BLK	2,000		
	893-566	LED Holder Rubber BLK	1,000		
	900-708	Felt (Speaker)	1,000		
	904-000	Felt Strip (E.S.C) Felt 175×6×1t	4,000		
	904-910	Felt 160×20×0.3t	1,000	BOTTOM COVER MIG	
	905-265	Felt φ18×φ4×0.5t BLK	6,000		
	905-385	Felt 20×X6×1t Sticker	2,000		
	2	510-57F-B	Front Body Ass'y	1,000	
		002-122-7	Resistor Carbonfilm 1.2K ohm 1/16W +5% "S"	1,000	R378
		130-101-8	Capacitor Ceramic 0.001μF 50WV	3,000	C1, 2, 3
		161-501-0	Capacitor Mica 15PF 50WV	1,000	C354
204-009-1		Transistor 2SC2078 (D)	1,000	Q415	
204-016-7		Transistor 2SC2314 (E)	1,000	Q413	
222-006-4		I.C KIA7217AP	1,000	IC5	
224-021-7		I.C LC7132	2,000	IC1, 2	
251-088-2		LED Lamp LTL-3233A GRN	13,000	LED4, 5, 6, 7, 9, 10, 11, 12, 13, 14, 15, 16, 17	
251-089-3		LED Lamp LTL-3273A Amber	2,000	LED18, 19	
251-090-3		LED Lamp LTL-3213A RED	6,000	LED 1, 2, 3, 8, 20, 21	
251-096-9		LED Lamp SLH-34MC3	2,000	LED22, 23	
252-034-8		LED Display LTD482Y-YF	2,000		
310-038-1		Coil RF Choke 22μF Bobbin	1,000	RFC416	
4A1-006-A		SW B'D PCB Ass'y	1,000		
401-283-A		P.C.B CH SW 49.5×50×1.6t 1/1	1,000		
401-284-A		P.C.B CH SW 57.5×50×1.6t 1/1	1,000		
401-397-A		P.C.B LED 75×33.5×1.6t 1/1 FR4	1,000		
420-707-6		Jack Earphone HSJ0615-01-010	2,000	J1, 2	
421-550-5		Connector Socket SW-1464	1,000		
421-551-6		Connector Socket SW-1332(R)	1,000		
430-018-0		Rotary SW GPS0477	2,000	SW2, 3	
431-045-9		Slide SW SHB22-104S 2P-2C	1,000	SW7	
431-121-4		Slide Switch SME-33-14.5 3P-3C	2,000	SW1, 9	
431-122-5		Slide Switch SSJ-022K 2P-2C	4,000	SW4, 5, 6, 8	
432-051-6		Push Switch SPUJ21 Lock-Release	1,000	SW11	
440-004-0		Mica (For T.R 2SC2078)	1,000		
440-005-1		Mica (For T.R 2SC2314)	1,000		
440-010-5		Mica (For I.C KIA7217AP)	1,000		
441-004-5		Bushing (For T.R 2SC2078)	1,000		
441-010-0		Bushing (For I.C KIA7217AP)	1,000		
450-401-8		Resistor Variable (VR) 10KB (WO/SW)	2,000	VR2, 4	
450-403-0		Resistor Variable (VR) 10KB (W/DPDT SW)	1,000	VR3	
450-601-2	Resistor Variable (VR) 50KB (WO/SW)	2,000	VR5, 6		

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.
	722-951	Bracket (Set MTG) SPC 1.6t BLK-Plate	1,000	
	731-940	Holder (MIC) ABS 94HB Black	1,000	
	740-510	Lever (MIC) ABS 94HB BLK	1,000	
	794-320	Name Plate (MIC) P.V.C 50.8 × 7.8 × 0.4t	1,000	
	880-740	Spring SUS304 WPA	1,000	
	893-190	Rubber Ring	1,000	
	910-306-A	MIC Box (Whistler-900) SW1S 209(W) × 89(D) × 53(H)	1,000	
	921-010-P	Polybag P.P 100 × 100 × 0.05t	1,000	
	923-030-P	Polybag P.P 300 × 300 × 0.05t	1,000	
	957-245	Label (Caution 3A)	2,000	
	910-267-A	Snow Box	2,000	
	910-268-A	Inner Box (Whistler-900) SW1	1,000	
	910-269-A	Out Box (Whistler-900) DW1	0.167	
	921-525-P	Polybag P.P 150 × 250 × 0.05t	1,000	
	935-715	Instruction Manual Whistler-900	1,000	
	940-171	Warning Card Nega Only	1,000	
	942-620	Service Station Card	1,000	
	942-685	Business Reply Mail Card	1,000	
	942-690	Trucks Magazine Card	1,000	
	956-915	Label (LEN LED) Sticker 123 × 10	1,000	
	956-920	Label (Display) Sticker 53 × 23	1,000	
5	510-57W-CA	Wire Cover Ass'y	1,000	
	427-045-6	Wire 1007 AWG 26(7/0.16) YEL	0,180	SP(+) (0.5:0.5)
	427-046-7	Wire 1007 AWG 26(7/0.16) GRN	0,180	SP(-) (0.5:0.5)
6	510-57W-FB	Wire Front Body Ass'y Whistler-900	1,000	
	427-001-6	Wire 1007 AWG 24(1/0.51) BLK	0,800	
	427-002-7	Wire 1007 AWG 24(1/0.51) BRN	0,130	
	427-003-8	Wire 1007 AWG 24(1/0.51) RED	0,460	
	427-004-9	Wire 1007 AWG 24(1/0.51) ORG	0,830	
	427-006-1	Wire 1007 AWG 24(1/0.51) GRN	0,360	
	427-007-2	Wire 1007 AWG 24(1/0.51) BLU	0,310	
	427-008-3	Wire 1007 AWG 24(1/0.51) VIO	0,570	
	427-010-4	Wire 1007 AWG 24(2/0.51) WHT	0,710	
	427-276-8	Vinyl Wire 26 (1/0.4) BLK	0,200	
7	510-57W-MA	Wire MIC Ass'y Whistler-900	1,000	
	427-045-6	Wire 1007 AWG 26(7/0.16) YEL	0,050	MIC-SW3 (0.5:0.5)
	427-046-7	Wire 1007 AWG 26(7/0.16) GRN	0,050	MIC-SW2 (0.5:0.5)
8	510-57W-MP	Wire Main P.C.B Ass'y Whistler-900	1,000	
	427-005-0	Wire 1007 AWG 24(1/0.51) YEL	0,180	J21-J21 (3:3)
	427-006-1	Wire 1007 AWG 24(1/0.51) GRN	0,270	J20 J20 (3:3)
	427-007-2	Wire 1007 AWG 24(1/0.51) BLU	0,260	J19 J19 (3:3)
	427-008-3	Wire 1007 AWG 24(1/0.51) VIO	0,160	J17-J17 (3:3)
	427-001-6	Wire 1007 AWG 24(1/0.51) BLK	0,680	
	427-002-7	Wire 1007 AWG 24(1/0.51) BRN	0,870	
	427-003-8	Wire 1007 AWG 24(1/0.51) RED	0,590	
	427-004-9	Wire 1007 AWG 24(1/0.51) ORG	1,360	
	427-010-4	Wire 1007 AWG 24(1/0.51) WHT	0,560	
	427-316-1	Shield Wire 1533 AWG 26(1/0.41-0.42) GRY	0,570	
9	427-174-9	Wire Strip 0.5 Dia	0,200	
10	960-371	Tube UL/CSA Keit-30 Vinyl AWG 2 (φ6.5) Clear	0,050	
11	964-052	Tube His 11M/M	0,100	
12	964-098	Tube Empire φ1	0,250	
13	965-020	Tape Scotch 20M/M (0.020 × 25M)	0,250	
14	965-039	Tape Packing PVC (0.05 × 25M)	0,500	
15	966-007	Solder Bar 63:37	20,000	
16	966-008	Solder Wire 60:40 (2.2 Dia)	0,002	
17	966-016	Solder Rosin Core Wire 60:40 0.04''-0.05''	30,000	
18	966-025	Flux Rosin	12,000	

Seq.	Part-No.	Part Name and Description	Q'ty	Reference-No.
19	966-034	Thinner For Flux	5,000	
20	966-061	Silicon Grease YG-6111 or XG-6111	1,000	
21	967-002	Stavilizer Material	50,000	
22	967-011	Bond #201	10,000	
23	967-048	Compound	2,000	
24	967-057	Wax Micro	10,000	
25	967-066	Wax Poly	5,000	
26	967-084	Screw Locking Paint AGP	2,000	
27	967-163	Tie Wire Vinyl 1.2 Dia	0,500	